

OPERATOR'S MANUAL

SAFETY RULES FOR THE PROFESSIONAL Stud Finder



WARNING:

Read all instructions before use. Failure to follow safety instructions may result in electric shock, fire. and/or serious injury and death.



WARNING:

TURN OFF all gas, water, and electric power before using any drilling or penetrating devices or equipment including drills, saws, routers, hammers, nails screws etc.

FAILURE TO TAKE THESE AND OTHER NECESSARY PRECAUTIONS COULD RESULT IN ELECTRIC SHOCK, FIRE, AND/OR SERIOUS INJURY AND DEATH.

Use extreme caution under these circumstances or whenever live wiring is present. Always turn off the electrical power, gas and water supplies before penetrating a surface.

FCC PART 15 CLASS B REGISTRATION WARNING

This device complies with Part 15 of FCC rules. Operation is subject to the following two conditions:

- 1. This device may not cause harmful interference, and
- 2. This device must accept any interference received, including interference that may cause undesired operation.

It is possible that there may be wood, metal, wiring, or other objects behind the surface that are not detected. The stud finder may also detect pipes, wires, or other objects that the user may not want it to detect. The stud finder is designed to detect any inconsistency but does not identify what type of inconsistency or object it detects. The illuminated LEDs may indicate the location of many different features including, but not limited to, studs, beams. water pipes, gas pipes, wires, an inconsistency in the surface material or paint, etc.

NOTICE:

The stud finder alone should not be relied upon exclusively to locate objects behind a scanned surface. Use other sources of information to help locate objects. Other sources of information may include, but are not limited to, construction plans, vis ar

SYMI

HART9PRO **PROFESSIONAL Stud Finder**

PRODUCT SPECIFICATIONS

Product Weight: 0.32 lbs Product Dimensions: 5.45 x 2.8 x 2.05 in.

ACCURATE

The multiple LEDs on the PROFESSIONAL Stud Finder track the location of studs to accurately and reliably identify the center and edges of studs simultaneously.


Just press and hold the button to instantly detect studs. No calibration required.

MULTI-SENSE TECHNOLOGY

The PROFESSIONAL Stud Finder has 9 sensors with Multi-Sense Technology. In comparison, conventional stud finders have 1 or 2 sensors. With more sensors, the PROFESSIONAL stud finder more accurately identifies the location of studs

TO OPERATE:

• Hold the stud finder by the detector outside of the handle area while scanning.



 Place the **PROFESSIONAL**

> Stud Finder firmly against the surface. Press and hold the "on" button.

- With the button depressed, you may immediately begin scanning the wall. (No calibration or tuning is required.) As you scan, LED lights will immediately display the location of any hidden objects.
- The PROFESSIONAL Stud Finder uses Active Learning Technology™. With Active Learning Technology™, the readings become more accurate the longer you hold the button while scanning the wall.
- On some surfaces, it may be helpful to slide the stud finder up and down to confirm the location of a stud.

HANDLE HOLD

TROUBLESHOOTING

CONDITION

When operating the PROFESSIONAL Stud Finder, the hand should remain on the handle. Holding the PROFESSIONAL Stud Finder on the sides may cause the unit to work inaccurately.

FEATURES

- 1. LED Lights
- 2. LIVE ELECTRICAL
- WARNINGT
- 3. Battery Cover
- 5. Detector Housing Sensor Board

4. Ergonomic Handle

7. "On" Button

SENSING THROUGH DIFFERENT MATERIALS:

Moisture

The scanned surface should be clean and dry. Paint and wallpaper need to be completely dry before scanning for studs. It may take up to 2 weeks for wallpaper to dry enough to detect studs.

Foil-Backed Insulation

Although not common, foil-backed insulation can cause inconsistent readings with all electronic stud finders. including the PROFESSIONAL Stud Finder.

Metallic Content in Wallpaper

Wallpaper with metallic content can block the detector's signals.

Textured Walls and Acoustic Ceilings

The PROFESSIONAL Stud Finder is capable of detecting studs through many textures and surfaces. The unit will however work most accurately if placed firmly against the flattest portions of the wall. For the best results, prior to beginning your scan, identify a horizontal area that is consistently the flattest.

Lath and Plaster

Irregularities in plaster thickness and variations in construction materials can make it difficult to locate studs behind lath and plaster walls. Also, the stud finder may not be able to detect if the plaster uses metal mesh reinforcement. Although many users have success, there is no guarantee the PROFESSIONAL Stud Finder will work on all lath and plaster walls.

Tile, Flooring, Roofing, and Exteriors

PROBABLE CAUSE

The PROFESSIONAL Stud Finder works by measuring the density of material behind the sensors to determine the location of studs. Due to the variability of density in tile flooring, roofing and exterior materials, we do not recommend the PROFESSIONAL Stud Finder for use in these applications

LIVE ELECTRICAL WARNING™

The PROFESSIONAL Stud Finder LIVE ELECTRICAL WARNING™ works continually while the button is depressed. When a live electrical wire is detected, the yellow lightning bolt symbol may illuminate to indicate the presence of live wires.

The PROFESSIONAL Stud Finder uses Active Learning Technology™. To best detect the presence of live electrical wires, slowly scan



in both directions, passing over the same location multiple times, for a more accurate reading.

NOTE: The PROFESSIONAL Stud Finder LIVE ELECTRICAL WARNING™ is optimized for finding live wires near studs.

WARNING: Use extreme caution under these circumstances or whenever live wiring is present. Always turn off the electrical power, gas and water supplies before penetrating a surface.

STICKERS / DECALS

Do not place decals or stickers, especially those containing metal, on the sensor board, or on the stud finder in any place.

DISASSEMBLY / PLASTIC PADS

Do not disassemble the stud finder or remove the plastic pads on the bottom. The stud finder will not operate correctly without the plastic pads properly in place.

Before turning on, ensure that the stud finder is clean and dry. If necessary, wipe the stud finder dry using a clean cloth. If the detector is wet or dirty it may not operate properly.

Temperature

If the stud finder is subject to a significant temperature change, allow it to adjust to the ambient temperature before using. The entire area of the sensor board should be at a similar temperature for best operation.

The PROFESSIONAL Stud Finder uses 2 AAA batteries. Do not mix old and new batteries. Do not mix alkaline, standard or rechargeable batteries. For best performance, use alkaline batteries only.

REPLACING THE BATTERIES

• Remove the battery cover by gently depressing on the right side and then lifting. Remove both batteries and dispose of them properly. Please recycle.

SOLUTION

- Replace with new AAA hatteries
- Close the battery cover by inserting the clip into the battery cavity, gently depress the other side of the battery cover inserting the other clip into the battery cavity until it clicks closed.

DISPOSAL

Stud finders and packaging should be sorted for recycling.

ENVIRONMENTAL CONDITIONS

HART stud finders will work best when maintained in the following environmental conditions:

Storage

(0°F to 120°F) Temperature (-18°C to 50°C) 0% to 90% Humidity

Relative humidity (non-condensing)

Operating (32°F to 110°F) Temperature

(0°C to 43°C) Humidity 0% to 90%

> Relative humidity (non-condensing)

LIMITED WARRANTY

Franklin Sensors warrants this product to be free from defects in material and workmanship for one year. This LIMITED WARRANTY does not cover products that are improperly used, abused, or altered. Defective products will be replaced or repaired. If a product is found to be defective within the warranty period, Franklin Sensors will, at its sole discretion, either repair or replace the defective product. This limited warranty does not apply to products that are subjected to freight damage, accident, abuse, alteration, misuse, improper repair, etc. Franklin Sensors and Franklin Sensors' authorized distributors shall bear no other liability or obligation under this warranty.

IN NO EVENT SHALL FRANKLIN SENSORS HAVE ANY LIABILITY FOR CONSEQUENTIAL OR INCIDENTAL DAMAGES INCLUDING, BUT NOT LIMITED TO, LOST PROFITS, DAMAGE TO GOODWILL, LOSS OF TIME, INCONVENIENCE OR OTHER COMMERCIAL OR ECONOMIC LOSS, and in no event shall Franklin Sensors be liable for damages exceeding the purchase price.

HART, the HART logo and H logo are trademarks of Techtronic Cordless GP and are used pursuant to a

In the event of a product defect, please return the product postage paid with proof of purchase to:

Franklin Sensors Inc. Attn: Returns Department 6675 N Pollard Ln. Meridian, ID 83646 (208) 918-2403 returns@franklinsensors.com Hours of Operation: Monday-Friday, 8 AM to 5 PM, Mountain Time Zone

US Patents 8,476,912 8,669,772 8,736,283 8,791,708 8,836,347 8,884,633 US and Foreign Patents Pending.

HART9PROF1 (12-2019)

and the form of the end of the contract of the					
visible points of entry of pipes, location of switches and outlets, and standard stud spacing practices.			No LED lights come on.	Weak battery.	Replace with 2 new AAA alkaline batteries. Do not mix old and new batteries.
YMBOL	SIGNAL	MEANING	Stud finder only works momentarily.	The "on" button isn't being held down.	Hold the "on" button down until you have completed your scan.
A		<u> </u>	The LED lights are indicating the location of pipes and wires, not just studs.	The PROFESSIONAL Stud Finder indicates the location of inconsistencies. The LED lights may indicate the location of a pipe, electrical wiring, other objects near the surface being scanned, or an inconsistency in the surface material or paint, etc.	Look for evenly placed studs on either side. Scan above the location and below the location to confirm results. Use caution before penetrating wall. See the SAFETY RULES FOR THE PROFES-SIONAL Stud Finder.
			Difficulty starting a scan near doors and windows.	Solid headers and triple studs are often present around doors and windows. The PROFESSIONAL Stud Finder indicates the change in density. If all the sensors sense the same density, the LEDs will not illuminate.	Begin the scan away from the window or door, then move the stud finder to the area around the window or door. For best results, keep stud finder 3"/7cm away from wood trim, outlets, switches, etc.
			Stud finder doesn't work through new wall paper.	The moisture in the wall after wall papering can block the stud finder's signal.	Wait until the wallpaper is dry. It may take up to 2 weeks for the paper to dry sufficiently.
Δ	LIVE ELECTRICAL WARNING™:	Indicates a hazardous situation, which, if not avoided, could result in death or serious injury.	My house was built prior to about 1960. The walls are lath and plaster. The stud finder doesn't work very well anywhere in my house.	Older houses that were built with lath and plaster, instead of sheet rock, often have too much inconsistency in the walls for the detector to work reliably.	Try using the stud finder at a higher point on the wall, or a lower point on the wall.
			Inconsistent readings.	Operator is holding the unit near the base rather than on the handle.	Only hold the unit by the handle with a finger continually pressing the button.
				Anomaly in the surface material.	Test at a higher location, or lower location on the wall.
	NOTICE:	Includes information		Sometimes after continuously scanning the wall for a period of time the readings seem to be less consistent.	Release the button and press the button again.
MUTICE.	considered important.	The LED lights sometimes appear to light up sporadically or inconsistently.	Wires, pipes, or other construction inconsistencies can cause erratic or erroneous readings. Features on the opposite side of a wall may also be a source of inconsistent readings.	Test at points on the wall that are higher, or lower. The stud finder may also work best if it is used more than 3"/7cm away from metal objects such as outlets, light switches, etc.	
				, ,	